

# M1 Voltage Meter



## Description

#	Specification
Display	7 segment LED display, 0.56
Digits	4 digit 1 row
Input Volts	0-500VAC (L-L)/(L-N)
Resolution	Auto ranging, Hz 0.01
PT Ratio	Upto 132 kV
Burden	3VA Max.
Auxiliary Supply	0.2 VA for voltage and current input
Update Time	1 Sec
Scroll	Auto / Manual
Parameters	Volts, TDH V

## Neptune India Ltd.

Neptune House, A 11 - Sector 59  
Noida - 201301, INDIA  
Tel: 0120 420 5900, 429 7900  
Email: [enquiry@neptuneindia.com](mailto:enquiry@neptuneindia.com)  
[www.neptuneindia.com](http://www.neptuneindia.com)